

THE EXPERTS' CHOICE

*Blazer*

**Line Interactive UPS**

A brilliant compact UPS for Your PC



Choose your UPS from Centralon-The company with worldwide reputation for combining Protection with Perfection

- Microprocessor control guarantees high reliability.
- Equipped with Boost and Buck AVR to stabilize input voltage.
- Built-in DC start function enables UPS to be started up without AC power supplied.
- Smart RS-232 Communication Port with Free Download Software from the Internet .
- Green Power Function for energy saving.
- Auto restart while AC recovery.
- Provides Modem/Phoneline Surge Protection.
- Provides Overload Protection.

## BLAZER LINE INTERACTIVE UPS SPECIFICATION

MODEL		Blazer 400	Blazer 600	Blazer 800
<b>CAPACITY</b>	VA/W	400VA/240W	600VA/360W	800VA/480W
<b>INPUT</b>	Voltage	115VAC or 220/230/240VAC		
	Voltage Range	85-140VAC / 162-290VAC		
<b>OUTPUT</b>	Voltage	115VAC or 220/230/240VAC		
	Voltage Regulation(Batt. Mode)	±10%		
	Frequency	50Hz or 60Hz		
	Frequency Regulation (Batt. Mode)	+/-1 Hz		
	Output Waveform	Modified Sinewave		
<b>BATTERY</b>	Battery Type & Number *	6V/4AH x 2pcs	12V/7AH x 1pc	12V/9AH x 1pc
	Back up Time (at a PC load with PII + 15" monitor)	12 minutes	33 minutes	34 minutes
	Recharge Time	8 hours to 90% after complete discharge		
<b>TRANSFER TIME</b>	Typical	2-6ms		
<b>INDICATOR</b>	AC Mode	Green lighting		
	Battery Mode	Green flashing		
<b>AUDIBLE ALARM</b>	Battery Mode	Sounding every 10 seconds		
	Low Battery	Sounding every second		
	Overload	Sounding every 0.5 second		
	Battery Replacement	Sounding every 2 seconds		
	Fault	Continuously sounding		
<b>PROTECTION</b>	Full Protection	Discharge, overcharge, and overload protection		
<b>PHYSICAL</b>	Dimension, DXWXH (mm)	330X100X140		
	Net Weight (kgs)	5	6	6.5
<b>ENVIRONMENT</b>	Operating Environment	0- 40 °C, 0-90 % relative humidity (non-condensing)		
	Noise Level	Less than 40dB		
<b>INTERFACE</b>	Smart RS-232	Support windows 95/98/NT/2000/XP, Novell, and Linux		

\* We will use equivalent type of batteries when mentioned batteries are in shortage.

\*\* Product specifications are subject to change without further notice.



# CENTRALION INDUSTRIAL INC

Address: 9F, NO. 135,Sec. 2, Ta-Tong Rd., Hsi-Chih, Taipei Hsien, Taiwan R.O.C.  
 Tel: 886-2-8692-6288 ( 20 Lines ) Fax:886-2-8692-6289  
 E-mail: sales@centralion.com  
 Home Page: <http://www.centralion.com>

